

# TX100

SINGLE BANKNOTE DETECTION

Thanking to its new technology the money detector **TX100** is able to recognize counterfeit banknotes from the genuine ones. **Small and handle**, it is perfect for places with a small space availability .

The usage is very intuitive: once inserted the banknote in the machine it will start a wide range of detects: magnetic ink,UV,infrared,banknote dimension and thickness of banknotes.In case of a suspected banknote the machine will reject the banknote by putting out 3 bip and it will be showed on the display the error code.

**The detector is 100% certified by the European Central Bank.**

## Features

Reading the banknote on any side and toward the insertion

Displaying of the EUR value inserted

Displaying the inserted pieces of banknotes

Displaying of the total amount in EUR inserted

Selection of the exit way of the banknotes

A bright signal to indicate the exit side of the banknote

Value: EURO

## Technical features

Dimensions: 155x137x82 mm

Weight: 0.5 kg

AC-voltage: AC100V~240V 50/60 HZ

DC-voltage: DC12V/1A

Using temperature: 0~45°C

Storage temperature: -20~65°C

Optional Litium Charger 11.1V/80mAH

Consumption: <10W

Speed: 0.5 second/sheet

Mini USB adapter included



Number of Banknotes

Banknotes value

On/Off

Clear/Report:

- displaying of the value of the single banknote
- number of banknotes
- displaying the total amount in EURO value

Exit way/Value

